## SNIA EUROPE STORAGE



# Managing iSCSI Adapters with VMware vSphere 4.1



STEVE ABBOTT SNIA Ethernet Storage Forum member, Emulex

One of the purposes of the SNIA Ethernet Storage Forum is to monitor technology trends in order to provide insights and educational resources to help businesses prepare for upcoming IT investments. By Steve Abbott, SNIA Ethernet Storage Forum member, Emulex.

One of the more impactful IT trends today is the rapid deployment of server virtualization. Server virtualization is being deployed on an almost universal scale to reduce costs and optimize data center resources. To underscore this point, a recent survey\* reported several key findings:

- Server virtualization is widely used 74% of respondents are currently using server virtualization and another 19% are planning deployments.
- The number of virtualized servers is relatively small today 58% of respondents have virtualized 30% or less of their servers
- The number of virtualized servers is growing the percentage of virtual machines (VMs) run in production will increase from 39% to 58% within two years

This trend is accelerating with new multi-core servers that support many more VMs per physical server and meet the requirements of resource-demanding, mission-critical applications.

As server capabilities grow, many data centers are finding their 1Gbps Ethernet (GbE) infrastructure is the next limiting factor for server virtualization. The solution is migration to 10Gbps Ethernet (10GbE) and the transition is gaining momentum as prices drop for 10GbE adapters and switches. Market availability of a 10X improvement in bandwidth is providing added incentive to support network and storage traffic on the same Ethernet infrastructure. Fibre Channel over Ethernet (FCoE) is a new technology to support block-based storage over Ethernet, but iSCSI is the established incumbent. Data centers have several options for 10GbE iSCSI server connectivity and iSCSI storage vendors are shipping 10GbE storage arrays to complete an end-to-end solution.

As part of this next-generation iSCSI environment, VMware introduced support for 10GbE iSCSI adapters with VMware vSphere 4.1. With this new capability, data center administrators may have questions about how to configure, manage and optimize iSCSI adapters with vSphere 4.1. The goal of this article is to provide answers to some of those questions.

## iSCSI Adapter Overview

In contrast to using iSCSI software initiators with a network interface card (NIC), iSCSI adapters present two devices per port to the vSphere 4.1 ESX hypervisor - a NIC and an iSCSI adapter. The NIC device can be used for any networking function while the iSCSI device is devoted exclusively to iSCSI storage traffic. The iSCSI device also supports offloading of iSCSI protocol processing from the server to the adapter.

\* ESG Research Report, The Evolution of Server Virtualization (November 2010)

# STORAGE | SNIA EUROPE

The NIC and iSCSI devices share the 10Gb bandwidth with a basic deployment and several server vendors provide the option to virtualize the physical port as three NICs and one iSCSI adapter. This allows bandwidth to be individually allocated to each of the four devices.

Separate drivers are required for the NIC and iSCSI functions. In most cases, the best practice is to download and install the most current driver that's available for the adapter, but it's important to confirm that drivers are qualified for the server and storage that will be used.

### Configuring iSCSI Adapter with VMware vSphere Client

The iSCSI device appears to ESX as a storage adapter and can be viewed in the vSphere Client under Storage Adapters in the Configuration tab.

The first step is to select Properties and the General tab to enable the adapter and assign the IP address.

The Dynamic Discovery tab can then be used to discover targets based on IP addresses.

The other option is to select the Static Discovery tab and manually enter information for the targets.

After completing setup for the adapter and discovery of the targets, a Virtual Machine File System (VMFS) volume needs to be created on a target LUN. Select a host, click on the

	4 (4 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 -	E (* <sup>1</sup> Element Assess) E Staarte Staar Staar Staar
Salah Balance Salah Salah Balance Salah Salah Balance Salah Salah Salah Salah Salah Salah Salah Salah Salah Salah Salah Salah		Particle         Image: Control of

Figure 2. Assigning the IP Address for iSCSI adapter

Configuration tab and choose Storage. Click the Add Storage wizard and select Disk/LUN for the storage type.When the wizard is completed, virtual machines (VMs) can be created on the VMFS datastore.

### **High Availability**

Most 10GbE adapters have two ports, which facilitate support for high availability using multipath I/O (MPIO). Best practices are to use fully redundant paths, including redundant adapters, cables, switches and array ports. If any of the components in the path fails, the host will automatically select another available path. With iSCSI adapters, the only requirement is to have multiple ports connected to the same iSCSI target.

Hardware	Storage Adapters						Refresh	Rescan Al
Processions	Device	Type	www				1	
Memory	🕥 vmhba34	ISCSI	kgn.1998-01.com	L VEWWARES	endex:2	55288870:36:		
Storage	🕑 vmba35	ISCSI	kgn.1998-01.com	Lymwares	emuleicti	031002631:37		
Networking	Emulex OneConnect							
Storage Adapters	🔘 vnihba2	GCSI	ign.1991-05.com					
Network Adapters	O verba3	6051	kgn.1991-05.com	LINCOGO	im Schi	7181129481		
Advanced Settings	Smart Array P410i							
Power Management	Details	million circa						2
Software CNS and Routing Authentication Services Power Nanagement Votual Machine Startus/Shutdown	SCSI Name: kgn ISCSI Alles:	ulex OneConnect 1991-05.com.microsoftx 0.190.2 Devices: 16	win-5ds7ubu29ke Paths: 64					Properties
CHS and Routing Authentication Services Power Hangement Virtual Machine Startup(Shutdown Virtual Machine Swapfile Location	Model: Em BCSI Name: kgn. BCSI Alles: P Address: 10. Connected Targets: 64 View: Devices: Paths	.1991-05.com.microsoft: .0.190.2 Devices: 16						Properties
DNS and Routing Authentication Services Power Hanagement Witual Hachine Startup(Shutdown Virtual Hachine Swapfile Location Security Profile	Model: Em BCSI Name: kgn. BCSI Alles: P Address: 10. Connected Targets: 64 View: Devices Patho Runtime Name Targe	1991-05.com.microsoft:x .0.190.2 Devices: 16 et	Paths: 64	LUN	State	-		
DNS and Routing Authentication Services Power Management Virtual Hachine Sketup(Shutdown Virtual Hachine Swapfile Location Security Profile System Resource Allocation	Model: Em 6CSI Name: kgn 6CSI Name: kgn 6CSI Alas: IP Address: 10. Connected Targets: 64 View: Devices Paths Runtime Name Targe vmbba3:c0:759.10 kgn.21	1991-05.com.microsoft: 0.190.2 Devices: 16 et 010-08.com.emuler.io.21	Paths: 64	0	Statu	Active		
DNS and Routing Authentication Services Power Hanagement Witual Hachine Startup(Shutdown Virtual Hachine Swapfile Location Security Profile	Modet Em 6CSI Name: Ign 6CSI Name: Ign 6CSI Name: Ign 6CSI Alas: IP Address: 10. Connected Targets: 64 View: Devices Paths Ruttine Name Targe vmhba3:c0:759.40 Ign.20 vmhba3:c0:759.40 Ign.20	1991-05.com.microsoft 0.190.2 Devices: 16 et 010-08.com.emder.io.21 010-08.com.emder.io.21	Paths: 64	0	Stahl	Active Active		
DNS and Routing Authentication Services Power Management Virtual Hachine Sketup(Shutdown Virtual Hachine Swapfile Location Security Profile System Resource Allocation	Modet Em GCSI Name: Ign GCSI Alias: IP Address: 10. Connected Targets: 64 View: Devices Paths Runtime Name Target withba3:C01759.L0 Gp.22 vmfbba3:C01749.L0 Gp.23	1991-05. com. microsoft:: .0.190.2 Devices: 16 010-08. com. emuler: io. 21 010-08. com. emuler: io. 21 010-08. com. emuler: io. 21	Paths: 64	0 0 0	9380 \$ \$	Active Active Active		
DNS and Routing Authentication Services Power Management Virtual Hachine Sketup(Shutdown Virtual Hachine Swapfile Location Security Profile System Resource Allocation	Modet Em BCSI Name: Ign BCSI Alias: IP PAddress: 10. Connected Targets: 64 View: Devices Paths Runtime Name Targe vmbba3:00:1791.0 kgn.20 vmbba3:00:1791.0 kgn.20 vmbba3:00:1791.0 kgn.20	1991-05. com. microsoft: 1 0.190.2 Devices: 16 010-08. com. emulex: io. 21 010-08. com. emulex: io. 21 010-08. com. emulex: io. 21 010-08. com. emulex: io. 21	Paths: 64	0 0 0	9381 0 0 0	Active Active Active Active		
DNS and Routing Authentication Services Power Management Virtual Hachine Sketup(Shutdown Virtual Hachine Swapfile Location Security Profile System Resource Allocation	Model: Em GCSI Name: Ign GCSI Name: Ign GCSI Name: Ign Connected Targets: 64 View: Devices Paths: Runtime Name Targe vmbba3:C0:T59:L0 Ign.20 vmbba3:C0:T59:L0 Ign.20 vmbba3:C0:T39:L0 Ign.20 vmbba3:C0:T39:L0 Ign.20 vmbba3:C0:T39:L0 Ign.20	1991-05. com. microsoft:1 (0.190.2 Devices: 16 010-08. com. emulex:io.21 010-08. com. emulex:io.21 010-08. com. emulex:io.21 010-08. com. emulex:io.21 010-08. com. emulex:io.21	Paths: 64	0 0 0 0 0 0 0 0	9.85 0 0 0	Active Active Active Active Active (1/0)		
DNS and Routing Authentication Services Power Management Virtual Hachine Sketup(Shutdown Virtual Hachine Swapfile Location Security Profile System Resource Allocation	Model: Em GCSI Name: kgn GCSI Name: kgn GCSI Name: kgn GCSI Alas: IP Address: 10, Connected Targets: 64 View: Devices Paths Runtime Name Targe vmbba3:c0:759.10 kgn.20 vmbba3:c0:759.10 kgn.20 vmbba3:c0:759.10 kgn.20 vmbba3:c0:7132.10 kgn.20 vmbba3:c0:7132.10 kgn.20	1991-05. com. microsoft: 0.190.2 Devices: 16 010-08. com. emulex: io. 21 010-08. com. emulex: io. 21	Paths: 64	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	92.8h	Active Active Active Active (1/0) Active (1/0)		
DNS and Routing Authentication Services Power Management Witual Hachine Skahup/Shutdown Virtual Hachine Swapfile Location Security Profile System Resource Allocation	Modet: Em 6CSI Name: Ign 6CSI Name: Ign 6CSI Name: Ign 6CSI Alas: IP Address: 10. Connected Targets: 64 View: Devices Patter Runtime Name Targe vmbba3:00:179:10 ign.20 vmbba3:00:173:10 ign.20 vmbba3:00:173:10 ign.20 vmbba3:00:1721:10 ign.20 vmbba3:00:1721:10 ign.20	1991-05. com. microsoft:1 (0.190.2 Devices: 16 010-08. com. emulex:io.21 010-08. com. emulex:io.21 010-08. com. emulex:io.21 010-08. com. emulex:io.21 010-08. com. emulex:io.21	Paths: 64	0 0 0 0 0 0 0 0	93.8h	Active Active Active Active Active (1/0)		

Figure 1. iSCSI adapter listed under Storage Adapters with VMware vSphere Client



Figure 3. Automatic discovery of iSCSI targets

#### **Boot from SAN**

Many data centers are deploying servers that will boot the ESX server from a target on the iSCSI storage array. This is particularly beneficial with blade servers that are often configured with no local disk storage. Boot from SAN (BFS) is supported with iSCSI adapters for both ESX and ESXi. The setup will be different for each manufacturer, but the basic procedure is to run software on the adapter to specify the target that will be used to install and boot the ESX hypervisor.

#### VMware VMotion Considerations

VMware VMotion is a key technology that allows a VM to be moved to a different physical server with no delays in service.

 Select Manage Type:
 Select Manage Type:

 Select Manage Type:
 Select Type:

 Select Type:

Figure 4. Creating a VMFS volume

Typical use cases include moving VMs to optimize workloads and to offload VMs for scheduled maintenance. VMotion is fully supported using NICs with software initiators and with iSCSI adapters, and they can be interchanged. For example, VMotion can be used to move a VM running on a server using a software initiator to a server using an iSCSI adapter. The only requirement is that both servers have access to the same-shared storage.

#### Using VLANs to isolate and optimize iSCSI traffic

A best practice for iSCSI storage includes separation of network and storage traffic. One option is to use separate physical networks. Another option is using Virtual LAN (VLAN) technology to create independent logical networks within a single physical network to isolate iSCSI traffic. Isolating network and storage traffic provides the following benefits:

- Security Only valid initiators can connect to the target storage array
- Latency Isolating the storage traffic typically results in a simplified network with fewer routers and associated latency
- Bandwidth All of the bandwidth can be used for storage traffic without being impacted by other network traffic

All the related components (initiator, switch and target) must include VLAN support when used for iSCSI. In addition to configuring the iSCSI initiator, the VLAN configuration must be applied to switch and target ports in the data path.

#### Summary

1141-1

With the release of vSphere 4.1, VMware has added support for 10GbE iSCSI adapters that simplify deployment of iSCSI connectivity for virtualized servers. iSCSI adapters present separate network and storage devices to the ESX hypervisor that can be managed using the VMware vSphere client. They also support key technologies that include high availability, boot from SAN, and isolation and optimization of storage traffic. Server virtualization deployed on new multi-core servers is driving the demand for increased networking and storage bandwidth and this requirement can be met effectively with 10GbE networks and iSCSI storage.

ni <b>Soli, Coli</b> Senat Indukti Convert 201 Jackst Regenting Receipting Receipting	Norman Frank <sup>10</sup> Robert M. M. Marketter Control of Real Model (Control, 2012), or local 2012 Bills, or second at a second VMT values <sup>10</sup> Roberts Mills Realismon Channel Mills Realismon Chan
	The Address of Adverse on Films ( Amond on 1923) of each the development of their that have a set in the developments

Figure 5. Creating a VM